

SPECIFICATION FOR LCD MODULE

Customer : _____
CustomerP/N _____
Model No. : RV042HDM-1500-30
Version : 00
Date : 2025-06-10

Final Approval by Customer

LCM Machinery OK ☐	Checked By	
LCM Display OK ☐	Checked By	
LCM NG ☐ LCM OK ☐	Approved By	

RJOYTEK Confirmed :

DESIGN	CHECK	APPROVAL

深圳市荣嘉毅科技有限公司 (RJOYTEK DISPLAY LTD)

Tel: (+86) 13510172564

EMAIL: danny@rjyi.net

Web: <http://rjoytek.en.alibaba.com>

Address: 深圳市宝安区航城大道航城智谷中城未来产业园 7 栋 301 室。

LIST OF CONTENTS

No.	CONTENTS	PAGE
1	REVISION HISTORY	
2	GENERAL INFORMATION	
3	ABSOLUTE MAXIMUM RATINGS	
4	DC ELECTRICAL CHARACTERISTICS	
5	TIMING CHARACTERISTICS	
6	RESET TIMING	
7	EXTERNAL DIMENSIONS	
8	INTERFACE SIGNALS	
9	ELECTRO-OPTICAL CHARACTERISTICS	
10	RELIABILITY TEST CONDITIONS	
11	INSPECTION CRITERION	
12	PRECAUTINGS FOR USING LCD MODULES	

1 REVISION HISTORY

Version	Date	Description	Revised By
V00	2025-06-10	First Issued	ZL

2 GENERAL INFORMATION

Item	Specification	Unit
LCD size 液晶面板尺寸	4.16	inch
Display Mode 显示模式	Normally Black	--
Resolution 分辨率	1280(RGB)x960	Pixel
Pixel pitch 像素尺寸	0.066(H) x 0.066(V)	mm
Pixel Arrangement 像素排列	RGB Vertical Stripe	
Viewing direction 视角	ALL	-
Module outline dimension	90.86(H)*72.84 (V)*3.8(D)	mm
LCM+CTP outline dimension	-	
LCD AA 液晶显示区域	48.6 (H)* 64.8 (V)	mm
TP VA 触摸可视区域	-	mm
Colors 颜色深度	16.7M	-
Weight 重量(TP+LCM)	-	g
Driver IC 驱动芯片	GH7005-01	-
Driver IC RAM Sise 记忆体	-	-
Interface 接口类型	MIPI	--
Backlight 背光类型	White LED	--
Touch IC 触摸芯片	-	--
Surface hardness 表面硬度	-	--
支持点数	-	--
Touch structure 触摸结构	-	--
Cover lens 盖板	-	--
Colors 颜色	-	--
Operating Temperature 工作温度	-20℃~ +70℃	--
Storage Temperature 存储温度	-30℃~ +80℃	--
环保要求	ROHS	--

3 ABSOLUTE MAXIMUM RATINGS

Parameter	Symbol	Min	Max	Unit	Note
Power Supply voltage 1	VCI~GND	-0.3	+4.6	V	
Power Supply voltage 2	IOVCC~GND	-0.3	+4.6	V	
Logic Input Voltage Range	V _{IN}	-0.3	IOVCC+0.5	V	
Logic Output Voltage Range	V _O	-0.3	IOVCC+0.5	V	

* The absolute maximum rating values of this product are not allowed to be exceeded at any times. Should a module be used with any of the absolute maximum ratings exceeded, the characteristics of the module may not be recovered, or in an extreme case, the module may be permanently destroyed.

4 DC ELECTRICAL CHARACTERISTICS

4.1 Driving TFT LCD Panel

AGND = GND = 0V, Ta = 25°C

Parameter	Symbol	Min	Typ	Max	Unit
Supply voltage for analog circuit	VCI	2.6	2.8	3.3	V
Supply voltage for logic circuit	IOVCC	1.65	1.8	3.3	V
Input voltage 'H'level	V _{IH}	0.7*IOVCC	—	IOVCC	V
Input voltage 'L'level	V _{IL}	GND	—	0.3*IOVCC	V
Output voltage 'H'level	V _{OH}	0.8*IOVCC	—	IOVCC	V
Output voltage 'L'level	V _{OL}	GND	—	0.2*IOVCC	V

4.2 Backlight Characteristics

Ta = 25°C

Item	Symbol	Min	Typ	Max	Unit	Condition
Forward voltage	V _f	-	15	-	V	
Luminance	LV	80	100	120	cd/m ²	
LED Life	Time		30000		Hour	
Number of LED	-	5X2			Piece	-
Connection mode	S/P	5Serial/2Parallel			-	-


Using condition: constant current driving method If= 2×60mA (+/-10%)

5 TIMING CHARACTERISTICS

TBD

6. Reset Timing

Signal	Symbol	Parameter	Min	Max	Unit
RESX	tRW	Reset pulse duration	10		uS
	tRT	Reset cancel		5 (note 1,5) 120 (note 1,6,7)	mS



Notes:

1. The reset cancel also includes required time for loading ID bytes, VCOM setting and other settings from EEPROM (or similar device) to registers.

This loading is done every time when there is HW reset cancel time (tRT) within 10 ms after a rising edge of RESX.


2. Spike due to an electrostatic discharge on RESX line does not cause irregular system reset according to the table below :

RESX Pulse	Action
Shorter than 5us	Reset Rejected
Longer than 9us	Reset
Between 5us and 9us	Reset starts

3. During the Resetting period, the display will be blanked(The display is entering blanking sequence, which maximum time is 120 ms, when Reset


Starts at Sleep-Out status. The display remains the blank state in Sleep-In mode). Then return to Default condition for Hardware Reset

4. Spike Rejection also applies during a valid reset pulse as shown below :



5. When Reset applied during Sleep-In Mode.
6. When Reset applied during Sleep-Out Mode
7. It is necessary to wait 10ms after releasing RESX before sending commands. Also Sleep Out command cannot be sent for 120 ms.

7. EXTERNAL DIMENSIONS



8 INTERFACE SIGNAL

Pin No.	Symbol	Description
1	LED-K	LED backlight cathode
2	LED-K	LED backlight cathode
3	LED-A	LED backlight anode
4	LED-A	LED backlight anode
5	NC	NC
6	GND	Ground
7	D0N	MIPI Data D0N
8	D0P	MIPI Data D0P
9	GND	Ground
10	D1N	MIPI Data D1N
11	D1P	MIPI Data D1P
12	GND	Ground
13	PCLKN	MIPI Data PCLKN
14	PCLKP	MIPI Data PCLKP
15	GND	Ground
16	D2N	MIPI Data D2N
17	D2P	MIPI Data D2P
18	GND	Ground
19	D3N	MIPI Data D3N
20	D3P	MIPI Data D3P
21	GND	Ground
22	GND	Ground
23	NC	NC
24	GND	Ground
25	TE	Frame head pulse signal
26	RESET	Reset signal pin (Active low)
27	IOVCC	Power supply to the internal logic 1.8V
28	VCC	Power supply to the internal Analog 2.8V
29	GND	Ground
30	GND	Ground


9 ELECTRO-OPTICAL CHARACTERISTICS

Item	Symbol	Condition	Min	Typ	Max	Unit	Note
Transmittance (w/o polarizer)	T%	$\theta=0^\circ$ $T_a=25^\circ\text{C}$	-	4.8	-	%	1
Contrast ratio	Cr		-	1200	-	-	3
Response time	Ton+Toff		-	30	35	ms	4
Surface Luminance	LV		1000	1500	-	cd/m ²	2
Viewing angle range	H or V er	Θ_{x+}	-	80	-	deg	5
		Θ_{x-}	-	80	-	deg	
		Θ_{y+}	-	80	-	deg	
		Θ_{y-}	-	80	-	deg	
CIE(x,y) chromaticity	Red	x	-	-	-	-	6
		y	-	-	-	-	
	Green	x	-	-	-	-	
		y	-	-	-	-	
	Blue	x	-	-	-	-	
		y	-	-	-	-	
	White	x	-	0.29	-	-	
		y	-	0.30	-	-	

Note 1. Ambient condition: $25^\circ\text{C}\pm 2^\circ\text{C}$, $60\pm 10\%\text{RH}$, under 10 Lunx in the darkroom.

Note 2. Measure device: BM-7A (TOPCON), viewing cone= 2°


Lv = Average Surface Luminance with all white pixels (P1,P2,P3,P4,P5)




Note 3. Definition of Contrast Ratio:

$$CR = \frac{\text{Average Surface Luminance with all white pixels (P1,P2,P3,P4,P5)}}{\text{Average Surface Luminance with all black pixels (P1,P2,P3,P4,P5)}}$$


Note 4. Definition of Response Time (Ton, Toff), The response time is defined as the time interval between the 10% and 90% amplitudes.



Note 5. Definition of view angle(θ , ψ):



Note 6. The LCD module should be stabilized at a given temperature for 20 minutes to avoid abrupt temperature change during measuring. In order to stabilize the luminance, the measurement should be executed after lighting Backlight for 20 minutes in a windless room. Measuring method for Contrast ratio, surface luminance, Luminance uniformity, CIE(x,y) chromaticity.



Light spot size $\varnothing = 7\text{mm}$, 500mm distance from the LCD surface to detector lens measurement instrument is TOPCON's luminance meter BM-7

10 📁 RELIABILITY TEST

Reliability test conditions (Polarizer characteristics null)

No.	Items	Condition	Inspection after test
1	High Temperature Storage	T = 80°C ± 2°C for 48 hr	Inspection after 4 hours storage at room temperature, the sample shall be free from defects: 1. Air bubble in the LCD 2. Sealleak; 3. Non-display; 4. missing segments; 5. Glass crack; 6. Current Idd is twice higher than initial value.
2	Low Temperature Storage	T = -30°C ± 2°C for 48 hr	
3	High Temperature Operating	T = 70°C ± 2°C for 48 hr	
4	Low Temperature Operating	T = -20°C ± 2°C for 48 hr (But no condensation of dew)	
5	High Temp. and High Humidity Operating	T = 60°C ± 5°C /90% for 24 hr (But no condensation dew)	
6	Thermal Shock	-20±2°C~25~70±2°C×10cycles (30min.) (5min.) (30min.)	
7	Dropping test (non-operation)	Drop to the ground from 76cm height, one time, every side of carton. (Packing condition)	
8	Packing Vibration (non-operation)	Frequency: 10Hz~55Hz~10Hz Amplitude: 1.0mm, X, Y, Z direction for total 3hours (Packing condition)	
9	ESD	Voltage: 2KV-6KV R: 330Ω C: 150pF Air discharge, 10time	

Note:

- (1) The test samples should be applied to only one test item.
- (2) Sample size for each test item is 5~10pcs.
- (3) In case of malfunction defect caused by ESD damage, if it would be recovered to normal state after resetting, it would be judge as a good part.
 Using ionizer(an antistatic blower) is recommended at working area in order to reduce electro-static voltage.
 When removing protection film from LCM panel, peel off the tag slowly (recommended more than one second) while blowing with ionizer toward the peeling face to minimize ESD which may damage electrical circuit.
- (4) Please use automatic switch testing mode when test operating mode.

11 📷 INSPECTION CRITERION

This specification is made to be used as the standard acceptance/rejection criteria for Normal LCM Product.

1 Sample plan

Sampling plan according to GB/T2828.1-2003/ISO 2859-1: 1999 and ANSI/ASQC Z1.4-1993, normal level 2 and based on:


Major defect: AQL 0.65

Minor defect: AQL 1.0

2. Inspection condition

Viewing distance for cosmetic inspection is about 30cm with bare eyes, and under an environment of 20~40W light intensity, all directions for inspecting the sample should be within 45° against perpendicular line. (Normal temperature 20~25°C and normal humidity 60±15%RH).

3. Definition of inspection zone in LCD.



Zone A: character/Digit area

Zone B: viewing area except Zone A (Zone A + Zone B=minimum Viewing area)

Zone C: Outside viewing area (invisible area after assembly in customer's product)

Fig.1 Inspection zones in an LCD.

Note: As a general rule, visual defects in Zone C are permissible, when it is no trouble for quality and assembly of customer's product.


4. Standards of inspection items

4.1 Major Defect

Item No	Items to be inspected	Inspection Standard	Classification of defects
4.1.1	All functional defects	1.No display	Major
		2.Display abnormally	
		3.Missing vertical, horizontal segment	
		4.Short circuit	
		5. Back-light no lighting, flickering and abnormal lighting.	
4.1.2	Missing	Missing component	Major
4.1.3	Outline	Overall outline dimension beyond the	





4.1.4	linearity	No more than 1.5%	
-------	-----------	-------------------	--

4.2 Cosmetic Defect

Item No	Items to be inspected	Inspection Standard				Classification of defects	
4.2.1	Clear Spots Black and white Spot defect Pinhole, Foreign Particle, polarizer Dirt	For dark/white spot, size Φ is defined as $\Phi = (x + y)/2$				Minor	
		1					
		Zone	Acceptable Qty				
			A	B	C		
		Size(mm)	Ignore				Ignore
		$\Phi \leq 0.15$	Ignore				
		$0.15 < \Phi \leq 0.20$	1				
		$0.20 < \Phi \leq 0.30$	0				
		$\Phi > 0.30$	0				
	Clear Spots TP Dirt	2				Minor	
		Zone	Acceptable Qty				
			A	B	C		
		Size(mm)	Ignore				Ignore
		$\Phi \leq 0.15$	Ignore				
		$0.15 < \Phi \leq 0.20$	1				
		$0.20 < \Phi \leq 0.30$	0				
		$\Phi > 0.30$	0				
		Dim Spots Circle shaped and dim edged defects	3				Minor
	Zone		Acceptable Qty				
			A	B	C		
	Size(mm)		Ignore			Ignore	
	$\Phi \leq 0.2$		Ignore				
	$0.20 < \Phi \leq 0.40$		1				
	$0.40 < \Phi \leq 0.60$		0				
	$\Phi > 0.60$		0				
Item No	Items to be inspected	Inspection Standard				Classification of defects	
4.2.2	Line defect	Size(mm)		Acceptable Qty		Minor	
		L(Length)	W(Width)	Zone			

	Black line, White line, Foreign material on polarizer			A	B	C	
		Ignore	W≤0.05	Ignore		Ignore	
		L ≤5.0	0.05<W≤0.08	2			
			W>0.08	0			
	Foreign material on TP film	The line can be seen after mobile phone in the operating condition:					Minor
		Size(mm)		Acceptable Qty			
		L(Length)	W(Width)	Zone			
				A	B	C	
		Ignore	W≤0.05	Ignore		Ignore	
		L ≤5.0	0.05<W≤0.08	3			
			W>0.08	0			
4.2.3	Dim line defect Polarizer scratch TP film scratch	If the scratch can be seen after mobile phone cover assembling or in the operating condition, judge by the line defect of 4.2.2. If the scratch can be seen only in non-operating condition or some special angle, judge by the following.					Minor
		Size(mm)		Acceptable Qty			
		L(Length)	W(Width)	Zone			
				A	B	C	
		Ignore	W≤0.03	Ignore		Ignore	
		5.0<L≤10.0	0.03<W≤0.05	2			
		L≤5.0	0.05<W≤0.08	1			
			W>0.08	0			
4.2.4	Polarize Air bubble	Air bubbles between glass & polarizer					Minor
		Zone Size(mm)		Acceptable Qty			
				A	B	C	
		Φ≤0.20		Ignore		Ignore	
		0.20<Φ≤0.3		2			
		Φ>0.30		0			

Item No	Items to be inspected	Inspection Standard	Classification of defects
---------	-----------------------	---------------------	---------------------------

4.35	Glass defect	(i) Chips on corner A:LCD Glass defect 	Minor						
		<table><tr><td>X(mm)</td><td>Y(mm)</td><td>Z(mm)</td></tr><tr><td>≤3.0</td><td>≤3.0</td><td>Disregard</td></tr></table>		X(mm)	Y(mm)	Z(mm)	≤3.0	≤3.0	Disregard
		X(mm)		Y(mm)	Z(mm)				
		≤3.0		≤3.0	Disregard				
		Notes: S=contact pad length Chips on the corner of terminal shall not be allowed to extend into the ITO pad or expose perimeter seal. B:TP Glass defect 							
		<table><tr><td>X(mm)</td><td>Y(mm)</td><td>Z(mm)</td></tr><tr><td>≤3.0</td><td>≤3.0</td><td>Disregard</td></tr></table>		X(mm)	Y(mm)	Z(mm)	≤3.0	≤3.0	Disregard
		X(mm)		Y(mm)	Z(mm)				
		≤3.0		≤3.0	Disregard				
		(ii) Usual surface cracks A:LCD Glass defect 							
		<table><tr><td>X(mm)</td><td>Y(mm)</td><td>Z(mm)</td></tr><tr><td>≤3.0</td><td><Inner border line of the seal</td><td>Disregard</td></tr></table>		X(mm)	Y(mm)	Z(mm)	≤3.0	<Inner border line of the seal	Disregard
		X(mm)		Y(mm)	Z(mm)				
		≤3.0		<Inner border line of the seal	Disregard				
B:TP Glass defect 									
<table><tr><td>X(mm)</td><td>Y(mm)</td><td>Z(mm)</td></tr><tr><td>≤6.0</td><td><2.0</td><td>Disregard</td></tr></table>	X(mm)	Y(mm)	Z(mm)	≤6.0	<2.0	Disregard			
X(mm)	Y(mm)	Z(mm)							
≤6.0	<2.0	Disregard							
(iii) Crack Cracks tend to break are not allowed. 									

12 📱 PRECAUTIONS FOR USE OF LCD MODULES

1. Handling Precautions

- (1) The display panel is made of glass and polarizer. As glass is fragile. It tends to become or chipped during handling especially on the edges. Please avoid dropping or jarring. Do not subject it to a mechanical shock by dropping it or impact.
- (2) If the display panel is damaged and the liquid crystal substance leaks out, be sure not to get any in your mouth. If the substance contacts your skin or clothes, wash it off using soap and water.
- (3) Do not apply excessive force to the display surface or the adjoining areas since this may cause the color tone to vary. Do not touch the display with bare hands. This will stain the display area and degraded insulation between terminals (some cosmetics are determined to the polarizer).
- (4) The polarizer covering the display surface of the LCD module is soft and easily scratched. Handle this polarizer carefully. Do not touch, push or rub the exposed polarizers with anything harder than an HB pencil lead (glass, tweezers, etc.). Do not put or attach anything on the display area to avoid leaving marks on. Condensation on the surface and contact with terminals due to cold will damage, stain or dirty the polarizer. After products are tested at low temperature they must be warmed up in a container before coming is contacting with room temperature air.
- (5) If the display surface becomes contaminated, breathe on the surface and gently wipe it with a soft dry cloth. If it is heavily contaminated, moisten cloth with one of the following solvents
 - Isopropyl alcohol
 - Ethyl alcoholDo not scrub hard to avoid damaging the display surface.
- (6) Solvents other than those above-mentioned may damage the polarizer. Especially, do not use the following.
 - Water
 - Ketone
 - Aromatic solventsWipe off saliva or water drops immediately, contact with water over a long period of time may cause deformation or color fading. Avoid contacting oil and fats.
- (7) Exercise care to minimize corrosion of the electrode. Corrosion of the electrodes is accelerated by water droplets, moisture condensation or a current flow in a high-humidity environment.
- (8) Install the LCD Module by using the mounting holes. When mounting the LCD module make sure it is free of twisting, warping and distortion. In particular, do not forcibly pull or bend the I/O cable or the backlight cable.
- (9) Do not attempt to disassemble or process the LCD module.
- (10) NC terminal should be open. Do not connect anything.
- (11) If the logic circuit power is off, do not apply the input signals.
- (12) Electro-Static Discharge Control, Since this module uses a CMOS LSI, the same careful attention should be paid to electrostatic discharge as for an ordinary CMOS IC. To prevent destruction of

the elements by static electricity, be careful to maintain an optimum work environment.

- Before remove LCM from its packing case or incorporating it into a set, be sure the module and your body have the same electric potential. Be sure to ground the body when handling the LCD modules.
- Tools required for assembling, such as soldering irons, must be properly grounded. Make certain the AC power source for the soldering iron does not leak. When using an electric screwdriver to attach LCM, the screwdriver should be of ground potentiality to minimize as much as possible any transmission of electromagnetic waves produced sparks coming from the commutator of the motor.
- To reduce the amount of static electricity generated, do not conduct assembling and other work under dry conditions. To reduce the generation of static electricity be careful that the air in the work is not too dried. A relative humidity of 50%-60% is recommended. As far as possible make the electric potential of your work clothes and that of the work bench the ground potential
- The LCD module is coated with a film to protect the display surface. Exercise care when peeling off this protective film since static electricity may be generated

(13) Since LCM has been assembled and adjusted with a high degree of precision, avoid applying excessive shocks to the module or making any alterations or modifications to it.

- Do not alter, modify or change the shape of the tab on the metal frame.
- Do not make extra holes on the printed circuit board, modify its shape or change the positions of components to be attached.
- Do not damage or modify the pattern writing on the printed circuit board.
- Absolutely do not modify the zebra rubber strip (conductive rubber) or heat seal connector.
- Except for soldering the interface, do not make any alterations or modifications with a soldering iron.
- Do not drop, bend or twist LCM.

2. Storage precautions

2.1 When storing the LCD modules, avoid exposure to direct sunlight or to the light of fluorescent lamps.

2.2 The LCD modules should be stored under the storage temperature range. If the LCD modules will be stored for a long time, the recommend condition is:

Temperature : 0℃ ~ 40℃ Relatively humidity: ≤80%

2.3 The LCD modules should be stored in the room without acid, alkali and harmful gas.

2.4 The LCD modules should be no falling and violent shocking during transportation, and also should avoid excessive press, water, damp and sunshine.

----- END